Manager: IP Office Configuration Mode > Editing Configuration Settings

Mergeable Settings

The table below shows the configuration entries for which changes can be merged and those that require a system reboot. The Send Configuration menu shown when sending a configuration to the IP Office automatically indicates when the configuration is mergeable.

Mergeable		3.2+	Pre-3.2
	System	–	–
	- System	✔*1	✘
	- LAN1/LAN2	✘	✘
	- DNS	✘	✘
	- Voicemail	✔*2	✘
	- Telephony	✔*3	✘
	- VoIP	✘	✘
	- LDAP	✘	✘
	- System Events	✘	✘
	- CDR/SMDR	✔	✘
	- Twinning	✔	–
	Line	✘	✘
	Control Unit	✘	✘
	Extension	✘	✘*4
	User	✔	✔
	Hunt Group	✔	✔
	Short Code	✔	✔
	Service	✔	✔
	RAS	✔	✔
	Incoming Call Route	✔	✔

Mergeable		3.2+	Pre-3.2
	WAN Port	✘	✘
	Directory	✔	✔
	Time Profile	✔	✘
	Firewall Profile	✔	✔
	IP Route	✔	✔
	Least Cost Route	✔	✔
	Account Code	✔	✔
	License	✔	✔
	Tunnel	✘	✘
	Logical LAN	✘	✘
	Wireless	✘	✘
	User Rights	✔	✔
	Auto Attendant	✔	✘
	Authorization Code	✔	✘
	ARS	✔	–
	E911 System	✘	✘

· ***1 - 3.2+ | System | System**
Changes to Locale, License Server IP Address and Favor RIP Routes over Static require a reboot.

· ***2 - 3.2+ | System | Voicemail**
Changes to Voicemail Type require a reboot.

· ***3 - 3.2+ | System | Telephony**
Changes to Companding LAW and Busy Tone Detection require a reboot.

· ***4 - 4.1+ | Extension**
For IP Office 4.1+, Base Extension and Disable Speakerphone are mergeable.

freedom from patent or any other protective rights of Avaya or others.

http://marketingtools.avaya.com/knowledgebase/businesspartner/ipoffice/mergedProjects/manager/html_mergeable_settings.htm

Last Modified: 21/01/2009